

PowerWave-8 Software updates Ver 8.72

1. System alerts (like detectors low battery or supervision) will appear as an event and a “ new event “ message will appear on the LCD , but after cheking in memory mode the message will not go off , only when he problem is fixed.
2. Default changes:
 - o P181E 5, 7 on
 - o P182E 5, 7 on
 - o P183E 5, 7 on
 - o P184E 5, 7 on

 - o P110E 4, 6, 7 on
 - o P120E 4, 6, 7 on

 - o P171E ALL ON
 - o P172E ALL ON
 - o P180E ALL ON

How to define the Telephone Report Option

Please follow this table . You must set the Report Option and scenario as describe in The table to Ensure Dialer operation correctly

Scenario	Report option	comments
Tel 1 : C.S Tel 2 : C.S (Backup)	P181E Options (1,5) P182E Options (1,5)	Stop , if Kiss off
Tel 1 : C.S Tel 2 : Domestic Tel 3 : Domestic	P181E Options (5) P182E Options (7) P183E Options (7)	Go next Tel Auto Kiss-off - on Call Progress -off
Tel 1 : Domestic Tel 2 : Domestic	P181E Options (7) P182E Options (7)	Auto Kiss-off - on Call Progress -off
Tel 1 : C.S Tel 2 : Voice Tel 3 : Voice	P181E Options (5) P182E Options (7) P183E Options (7)	Go next Tel
Tel 1 : Voice Tel 2 : Voice	P181E Options (7) P182E Options (7)	Stop , if Kiss off